



Data sheet
Fiche produit

POWERTOOL BATTERY BATTERIE OUTILLAGE ELECTROPORTATIF

AML90452



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX	
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible	
TECHNOLOGY	TECHNOLOGIE	Lithium-ion	
CAPACITY	CAPACITÉ	2	Ah
VOLTAGE	TENSION	14,4	V
POWER	PUISSANCE	28,8	Wh
CHARGING CURRENT	COURANT DE CHARGE	3	A (max 4A)
DIMENSIONS	DIMENSIONS		
• Length	• Longueur	113	mm
• Width	• Largeur	82	mm
• Height	• Hauteur	88	mm
WEIGHT	POIDS	330	g

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766671981	
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT		
• Charging	• Chargement	0°C + 45°C	
• Discharging	• Décharge	- 10°C + 55°C	

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

PART NUMBER	Non-exhaustive list / Liste non exhaustive			
	130111073	BPP1417	130171001	130224024
	5133001102	BPL1414	BPP-1413	BPP-1415
	BPP-1417	BPP1413	BPP1415	

Ryobi 14.4 V (BPL1414, B-1415-S, B-1442T, CHD1442, LCDI1402, LCDI14022, LCDI14022B, LCD1402, LCD14022, LLCD 14022LLCD14021, 130111073, 130224010, 130224011, 130224017, 130245005, 1311166, 1314702, 130281002, CDDI14022N, CDDI14022NF, CDD144V22, CHD1441, 13225471400144, 1400655, 1400656, 1400669, 1400670, 1400671, 4400011,

FIT MODEL

MARQUES MODÈLES

COMPLEMENTARY PRODUCTS / PRODUITS COMPLEMENTAIRES*

CHARGER	CHARGEUR	CEL1T14
BATTERY	BATTERIES	AML9069 - Batterie outillage électroportatif compatible Ryobi 14,4V 1.5Ah

www.enix-energies.com - 12/06/2024

1/1

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

