



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX	
TYPE OF CHARGER	TYPE DE CHARGEUR	Compatible	
TECHNOLOGY	TECHNOLOGIE	Lithium-ion	
INPUT VOLTAGE	TENSION D'ENTRÉE	100-240 V	50-60 Hz
OUTPUT VOLTAGE	TENSION DE SORTIE	18 V	
OUTPUT CURRENT	COURANT DE SORTIE	3A±0.3A	A
OUTPUT POWER	PUISSANCE DE SORTIE	73 W	
DIMENSIONS	DIMENSIONS		
• Length	• Longueur	150	mm
• Width	• Largeur	115	mm
• Height	• Hauteur	90	mm
WEIGHT	POIDS	604	g

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766468093
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT	
• Charging	• Chargement	0°C + 40°C
STORAGE TEMPERATURE	TEMPÉRATURE DE STOCKAGE	-20°C+60°C
LED	LED	
• Standby	• Prêt	Blinking green light
• Charging	• Chargement	Red light is on, greenlight is off
• Full charged	• Charge complète	Green light is on, red light is off
• High/low temperature protection	• Protection contre les températures élevées/basses	Blinking red at 1Hz
• Defective battery indicator	• Indicateur de batterie défectueuse	Blinking red and green alternately at 1Hz
• The charger is faulty	• Chargeur est défectueux	Orange indicator blinks at 3Hz
LOADING TIME	Temps de chargement	
• Time out stop	Arrêt automatique de sécurité	Stop charging if the charging time exceeds 3 hours ±20 minutes

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES

PART NUMBER	PART NUMBER	2607225322230
		AL 1860 CV
FIT MODEL	MARQUES	Bosch BAT607
	MODÈLE	Bosch BAT614
		Bosch BAT609
		Bosch BAT618
		Bosch 2607336150

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

