



Data sheet
Fiche produit

POWERTOOL BATTERY BATTERIE OUTILLAGE ELECTROPORATIF

AML90100CC



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX	
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible	
TECHNOLOGY	TECHNOLOGIE	Lithium-ion	
CAPACITY	CAPACITÉ	4	Ah
VOLTAGE	TENSION	14,4	V
CHARGING CURRENT	COURANT DE CHARGE	4	A (max 4A)
DIMENSIONS	DIMENSIONS		
• Length	• Longueur	96	mm
• Width	• Largeur	71	mm
• Height	• Hauteur	66,5	mm
WEIGHT	POIDS	455	g

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766645296	
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT		
• Charging	• Chargement	0°C + 45°C	
• Discharging	• Décharge	- 20°C + 60°C	

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

Non-exhaustive list / Liste non exhaustive

PART NUMBER	196388-5
	194065-3
	1940653
	194066-1
	1940661

FIT MODEL

MARQUES MODÈLES

Makita 14,4 V (BBO140 ,
BCF050,BFR750,BL1415,BL1430,CJ100D,DAROWA,DCF300,HP347DWEX3,MT080E,TS130DRFX,TD126D,LXT200, KP140DZ,
BL1440,JT6226,LGG1230,LGG1430,MAK1430LI,MET1821)

www.enix-energies.com - 15/10/2025

1/1

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

