



Data sheet
Fiche produit

VACUUM CLEANER BATTERY BATTERIE ASPIRATEUR

AML90302



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX	
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible	
TECHNOLOGY	TECHNOLOGIE	Lithium-ion	
VOLTAGE	TENSION	21,6	V
CAPACITY	CAPACITÉ	2	Ah
POWER	PUISSANCE	43,2	Wh
CHARGING CURRENT	COURANT DE CHARGE	2	A (max 4A)
DIMENSIONS	DIMENSIONS		
• Length	• Longueur	131	mm (5.16 inches approx)
• Width	• Largeur	81	mm (3.19 inches approx)
• Height	• Hauteur	122	mm (4.8 inches approx)
WEIGHT	POIDS	408	g (0.9 lbs)

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766632517	
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT		
• Charging	• Chargement	0°C + 45°C	
• Discharging	• Décharge	- 10°C + 55°C	

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

Non-exhaustive list / Liste non exhaustive

PART NUMBER	968670-02	968670-03	DYSON 225403	DYSON 968670-02	DYSON 968670-03
FIT MODEL	MARQUES MODÈLE		SV11	V7 Car+Boat	V7 Motorhead Pro
			V7	V7 Extra	V7 Motorhead vacuum
			V7 Animal	V7 Fluffy	V7 Total Clean
					V7 Trigger

www.enix-energies.com - 07/04/2025

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

