



Data sheet
Fiche produit

POWERTOOL BATTERY BATTERIE OUTILLAGE ELECTROPORTATIF

AML90366



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX	
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible	
TECHNOLOGY	TECHNOLOGIE	Lithium-ion	
CAPACITY	CAPACITÉ	4	Ah
VOLTAGE	TENSION	36	V
POWER	PUISSANCE	144	Wh
DISCHARGING CURRENT	COURANT DE DÉCHARGE	30	A
DIMENSIONS	DIMENSIONS		
• Length	• Longueur	156,99	mm
• Width	• Largeur	79,8	mm
• Height	• Hauteur	73,5	mm
WEIGHT	POIDS	1135	g

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766648679	
OPERATING TEMPERATURE	TEMPÉRATURE DE FONCTIONNEMENT		
• Charging	• Chargement	0°C - 45°C	
• Discharging	• Décharge	- 20°C - 60°C	

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

Non-exhaustive list / Liste non exhaustive

PART NUMBER	15225027	1600A001T2	1600A0022N	2607336003	2607336004
FIT MODEL	MARQUES MODÈLE				
	Bosch 36V - AHS 54 Li-Ion		Bosch 36V - GBH 36 V-LI		
	Bosch 36 V - AKE 30 Li Li-Ion		Bosch 36V - GHE 36 V		
	Bosch 36V - GBA 36V		Bosch 36V - GFR 25 Professional		

www.enix-energies.com - 08/09/2025

1/1

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

