



Data sheet
Fiche produit

POWERTOOL BATTERY BATTERIE OUTILLAGE ELECTROPORTATIF

AML90455



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX		
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible		
TECHNOLOGY	TECHNOLOGIE	Lithium-ion		
CAPACITY	CAPACITÉ	18	V	
VOLTAGE	TENSION	1,5	Ah	
POWER	PUISSANCE	27	Wh	
CHARGING CURRENT	COURANT DE CHARGE	2	A	(max 4A)
DIMENSIONS	DIMENSIONS			
• Length	• Longueur	140	mm	
• Width	• Largeur	78	mm	
• Height	• Hauteur	70	mm	
WEIGHT	POIDS	415	g	

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766673817		
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT			
• Charging	• Chargement	0°C + 45°C		
• Discharging	• Décharge	- 10°C + 55°C		

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

Non-exhaustive list / Liste non exhaustive

PART NUMBER								
	244760-00	A14F	B8236	FS120B	HPB14	A14	A9276	
	499936-34	A1712	BD-1204L	FS120BX	HPB14-CA	A144	B-8315	
	499936-35	A1718	BD-1444L	FS140BX	HPB18	A144EX	B-8316	
	90534824	A18	BD1204L	FS180BX	HPB18-OPE	FSB12	BPT1058	
	A12	A9251	BD1444L	FS18BX	NST2118	FSB18	EZWA77	
	A12-XJ	A9262	BPT1047	FS18FL	PS140	HPB12	EZWA80	
	A12EX	A9274	BPT1048	FSB 14	PS140A			

BLACK & DECKER 18V

FIT MODEL

MARQUES MODÈLES

FIRESTORM 18V

COMPLEMENTARY PRODUCTS / PRODUITS COMPLÉMENTAIRES*

BATTERY	BATTERIES	AMH90131 - Batterie outillage électroportatif compatible Black & Decker / Firestorm 18V 1.5Ah
----------------	------------------	---

www.enix-energies.com - 07/01/2025

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

