



Data sheet
Fiche produit

POWERTOOL BATTERY BATTERIE OUTILLAGE ELECTROPORTATIF

AML90457



MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX	
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible	
TECHNOLOGY	TECHNOLOGIE	Lithium-ion	
VOLTAGE	TENSION	18	V
CAPACITY	CAPACITÉ	6	Ah
POWER	PUISSANCE	108	Wh
CHARGING CURRENT	COURANT DE CHARGE	2	A (max 6A)
DIMENSIONS	DIMENSIONS		
• Length	• Longueur	115,8	mm
• Width	• Largeur	80,3	mm
• Height	• Hauteur	64,9	mm
WEIGHT	POIDS	650	g

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766673879
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT	
• Charging	• Chargement	0°C + 45°C
• Discharging	• Décharge	- 10°C + 55°C

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

Non-exhaustive list / Liste non exhaustive

PART NUMBER	1 600 A00 5B0	1.600.A00.DD7	2607335040	2607336208
	1 600 A00 DD7	1.600.A01.1T8	2607336039	2607336921
	1 600 A01 1T8	1600Z00000	2607336040	2607337199
	1.600.A00.5B0	2531 AD	2607336207	

FIT MODEL

MARQUES MODÈLE

All Bosch Power for All 18V

COMPLEMENTARY PRODUCTS / PRODUITS COMPLÉMENTAIRES*

BATTERY	BATTERIES	AML9003 - Batterie universelle compatible Bosch Power for All 18V 3Ah
		AML90456 - Batterie universelle compatible Bosch Power for All 18V 4Ah

www.enix-energies.com - 22/10/2024

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only, consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

1/1

